TECHNICAL INFORMATION

Machine Type	Zip payment system	Model	Reader	T.I. Number: 04011601	
				Issued by Steve Dolman	
Part numbers	Not applicable			Date	16th January 2004
Subject	Programming a Zip reader that has reset to default			ISSUED FOR CUSTOMERH	
				ACTION	
				INFORMATION	X

TO ALTER LANGUAGE

1. Connect programmer – Programmazione
2. Press **[Ent]** (Enter) Prezzi Vendita
3. Press **F4** until ..... Altri Parametri
4. Press **[Ent]** Credito Caribac
5. Press **F4** until ..... Lingua Italiano
6. Press **[Ent]**
7. Press **F4** until ..... Lingua English
8. Press **[Ent]** twice to confirm
9. Press **[CLR]** until Programming

TO CONFIGURE PAYMENT SYSTEM "EXECUTIVE or Protocol-A"

Note: Use F4 to scroll, CLR to exit menu and ENT to enter menu, ENT must be pressed twice to save any changes made to set-up

If the ZIP system is fitted to an executive machine the settings must be as follows.

1. Connect programmer, press enter, scroll to **Machines**, press enter twice and select **system type *executive*, if no coin mechanism is fitted, or *change-giver* if coin mechanism is also fitted.** Press enter **twice** to confirm any changes made.
2. Press f4 and set **Sale type to Multiple**.
3. Press f4 and select **Protocol Price on VMC**
4. Press f4 and scroll to **Decimal Point** and set to **D** (you may need to set to **C** for certain machines)

Sales prices can now be set on the machine in the normal way

TECHNICAL INFORMATION

Machine Type	Zip payment system	Model	Reader	T.I. Number: 04011601	
				Issued by Steve Dolman	
Part numbers	Not applicable			Date	16th January 2004
Subject	Programming a Zip reader that has reset to default			ISSUED FOR CUSTOMERH	
				ACTION	
				INFORMATION	X

TO CONFIGURE PAYMENT SYSTEM "MDB"

Note: Use F4 to scroll, CLR to exit menu and ENT to enter menu, ENT must be pressed twice to save any changes made to set-up

1. Connect programmer, press enter, scroll to **Machines**, press enter twice and select **system type** ***MDB***. Press enter **twice** to confirm any changes made.
2. Press f4 and set **Sale type to Multiple**.
3. Press f4 and select **Price on VMC**
4. Press f4 and scroll to **Decimal Point** and set to **C**
5. Press f4 and scroll to **Country Code**. Set this to **0044** (UK) and press Enter twice to store it.
6. Press CLR until '**PROGRAMMING**' appears on the display.
7. Sales prices can now be set on the machine in the normal way.

To set up BONUS or FREE VEND

1. Connect programmer
2. Press F4 until display reads **AUX** and press enter.
3. If required press enter to set Time and Date, if not press F4 and scroll to Bonus
4. Press enter, display will read **Bonus 1.**
5. Press enter, set **USE** to **Recharge and Sale** by pressing enter, and use F4 to scroll and press enter twice to confirm change.
6. Press F4, display reads **Enable Keys**
7. Press enter, press enter and use F4 to set level 0 to ON, press enter twice to confirm change.
8. Press clear (CLR), display reads **Enable keys**, press F4
9. Press enter, use F4 to set **Period** to **Day**, press enter twice to confirm.
10. Press F4, display reads **Type/Value**
11. Press enter, press enter again and use **F4** to scroll to **Token**, press enter twice to confirm.
12. Press F4, display reads **Discount Level 0 = 0**
13. Press enter and key in number of free vends required for example 2, press enter twice to confirm.
14. Each key will now receive the number of free vends set above. **Note all keys are set to level 0 as default**.